

A6Y-2B

1-1/2" X 13/32" MIDGET FUSES



A6Y "Type 2B" Amp-trap® midget fuses are fast acting on short circuits, yet have sufficient time delay to offer supplemental protection for small motors, transformers, and control circuits. (Not for Branch Circuit Protection).

Features/Benefits

- Moderate amount of time delay for circuits with inrush characteristics
- **Fast acting** on short circuits
- Can be used with **ULTRASAFE™** fuse holders

HIGHLIGHTS:

- Fast Acting

APPLICATIONS:

- Supplemental protection of 600V (up to 3A) and 500V (3-2/10-15A) AC circuits
- Small motors, transformers, and control circuits

Ratings

- **AC:** 1/4 to 3A
600VAC, 10kA I.R.;
- 3-2/10 to 15A
500VAC, 10kA I.R.

Approvals

- Ferraz Shawmut Inc. Certified

Standard Fuse Ampere Ratings, Catalog Numbers

| AMPERE RATING | CATALOG NUMBER | AMPERE RATING | CATALOG NUMBER |
|---------------|----------------|---------------|----------------|
| 1/4 | A6Y1/4-2B | 3-2/10 | A6Y3-2/10-2B |
| 1/2 | A6Y1/2-2B | 3-1/2 | A6Y3-1/2-2B |
| 6/10 | A6Y6/10-2B | 4 | A6Y4-2B |
| 8/10 | A6Y8/10-2B | 5 | A6Y5-2B |
| 1 | A6Y1-2B | 6 | A6Y6-2B |
| 1-1/4 | A6Y1-1/4-2B | 7 | A6Y7-2B |
| 1-1/2 | A6Y1-1/2-2B | 8 | A6Y8-2B |
| 1-6/10 | A6Y1-6/10-2B | 9 | A6Y9-2B |
| 2 | A6Y2-2B | 10 | A6Y10-2B |
| 2-1/2 | A6Y2-1/2-2B | 12 | A6Y12-2B |
| 3 | A6Y3-2B | 15 | A6Y15-2B |

**Melting Time – Current Data 1/4 - 3 Amperes, 600 Volts AC
3-2/10 - 15 Amperes, 500 Volts AC**

